


**Deep Housing - Standard MR16, PAR36/AR111, PAR20/PAR30, GU10**



**Remote Transformer/Line Voltage Installation**



**NEEDED FOR INSTALLATION:**

- 1/8" Allen Wrench
- Waterproof Wire Connectors
- Level
- Phillips Screwdriver
- 7/8" Hole Saw

**INSTRUCTIONS PERTAINING TO A RISK OF FIRE, OR INJURY TO PERSONS IMPORTANT SAFETY INSTRUCTIONS**

**Lighted fixture is HOT!**

**WARNING - To reduce the risk of FIRE OR INJURY TO PERSONS:**

Turn off/unplug and allow to cool before replacing LED. Fixture gets HOT quickly! Contact only switch/plug when turning on. Do not touch hot lens, guard, or enclosure. Keep fixture away from materials that may burn. Do not operate the luminaire fitting with a missing or damaged shield. Do not touch the source at any time. Use a soft cloth or gloves. Oil from skin may cause damage.

**SAVE THESE INSTRUCTIONS**


**IMPORTANT SAFETY INFORMATION - READ, FOLLOW, AND SAVE ALL SAFETY AND INSTALLATION INSTRUCTIONS**

- Product must be installed by a qualified person in a manner consistent with its intended use and in compliance with the National Electrical Code, Canadian Electrical Code, and all Local and Provincial Codes.
- Follow product label information and instructions.
- Qualified Personnel with appropriate personal protective equipment must perform all servicing of this product.
- Before wiring to power supply and during servicing, turn off and lock out power at fuse or circuit breaker before service.
- The use of accessory equipment not recommended by the manufacturer or installed contrary to instructions may cause an unsafe condition. The use of damaged components may cause an unsafe condition and void product warranty.
- Do not block light emanating from product in whole or part, as this may cause an unsafe condition.
- Never operate the fixture with missing or damaged lens. Lens must be cleaned on regular basis.
- Entire fixture may become extremely hot. Do not touch hot lens or fixture body.
- Replace LED assembly only with correct wattage and type of power supply appropriate for LED assembly.
- All gaskets, o-rings and sealing surfaces must be kept clean during installation and service; failure to do this may cause an unsafe condition and void product warranty.


**IMPORTANT LISTINGS AND CERTIFICATIONS**

- Suitable for wet locations • Suitable for recessed in ground locations


Proper soil preparation is recommended before installation. See the DIG-IT guide at [www.bklighting.com/collaterals/install/digit.pdf](http://www.bklighting.com/collaterals/install/digit.pdf) for more information.



**Soil Prep**



- A. Determine Soil Type by referencing DIG-IT Guide.
- B. Dig hole 18" wide and 20" deep.



- C. Prep soil according to DIG-IT Guide.

**IMPORTANT SAFETY INFORMATION - READ, FOLLOW, AND SAVE THESE INSTALLATION INSTRUCTIONS**

**B-K LIGHTING**


40429 Brickyard Drive • Madera, CA 93636 • USA  
 559.438.5800 • FAX 559.438.5900  
[www.bklighting.com](http://www.bklighting.com) • [info@bklighting.com](mailto:info@bklighting.com)

RELEASE DATE  
 10/13/2021




REFERENCE NUMBER  
 INS-2851-00

THIS DOCUMENT CONTAINS PROPRIETARY INFORMATION OF B-K LIGHTING, INC. AND ITS RECEIPT OR POSSESSION DOES NOT CONVEY ANY RIGHTS TO REPRODUCE, DISCLOSE ITS CONTENTS, OR TO MANUFACTURE, USE OR SELL ANYTHING IT MAY DESCRIBE. REPRODUCTION, DISCLOSURE OR USE WITHOUT SPECIFIC WRITTEN AUTHORIZATION OF B-K LIGHTING, INC. IS STRICTLY FORBIDDEN.

Remote Transformer/Line Voltage Installation



Housing Installation






1. Connect branch conduit connectors (not included) to the junction box using either the threaded conduit entries on the bottom of the junction box or through holes drilled into the sides of the junction box.

2. Place housing in hole. Align junction box in the path of the conduit trench.

3. Insert four (4) pieces of 1/2" EMT conduit through the Stability Flange. Hammer into substrate until secure.

⚠️ Recommend 7/8" drill bit for side installation.




⚠️ Leave sufficient clearance to elevate housing to finished grade.



4. Raise housing on EMT so housing is flush with finished grade. Use a level to aid in housing installation.

5. When housing is level, tighten screws on Stability Flange to secure housing to EMT. Remove excess EMT as needed.

6. Pull primary branch circuit wiring into junction box.



7. Per DIG-IT Guide, backfill the gap between the bottom of housing and bottom of hole with sand for drainage.

8. **For soil installation:** Fill and tamp soil to the appropriate height leaving room for sod, pavers, etc. to be level with the top of the temporary cover.


9. **For concrete installation:** Fill the hole around the fixture housing to 12" below the finished grade with clean fill dirt and tamp carefully to prevent settling of fixture. Pour concrete and finish as required flush with the top surface of the temporary cover.

⚠️ Soil installation is not drive-over rated.

**IMPORTANT SAFETY INFORMATION LISTED ON REVERSE  
READ, FOLLOW, AND SAVE ALL SAFETY AND INSTALLATION INSTRUCTIONS**




*Remote Transformer/Line Voltage Installation*




**Installation**



1. Remove temporary cover.




2. Make watertight connections using waterproof wire connectors (provided) to leads on the bottom of Patented HydroLock Barrier Plate Assembly. **See wiring diagram.**




**WIRING DIAGRAM FOR USE WITH:**

- MR16
- PAR36/AR111




**WIRING DIAGRAM FOR USE WITH:**

- GU10
- PAR20/PAR30




3. Wipe inside of housing where HydroLock plate will sit clean of debris before inserting patented HydroLock plate on to junction box. Align HydroLock plate with pins in housing and seat it firmly in place.




4. Turn HydroLock Barrier Plate clockwise ¼" to lock.


**⚠ Patented HydroLock Barrier Plate must be completely seated to ensure proper seal or water may intrude. This step must be done as stated or you will void your warranty.**



5. Connect optiLock assembly to Patented HydroLock Barrier plate with quick disconnect.



3. Place OptiLock in CO2 housing and align keyhole notch under one of three (3) #8 screw heads. Rotate horizontally to desired aiming position, then tighten two (2) #8 Phillips screws using Phillips screwdriver. Install proper MR16 halogen, PAR36/AR111, PAR20/30, or GU10 lamp according to instructions on Lamp Installation Or Re-Lamping page.



**FOR USE WITH MR16**

7a. Aim vertically by turning the thumbscrew on OptiLock assembly.



**⚠ OptiLock vary by product.**

**IMPORTANT SAFETY INFORMATION LISTED ON REVERSE  
READ, FOLLOW, AND SAVE ALL SAFETY AND INSTALLATION INSTRUCTIONS**




**Deep Housing - Standard MR16, PAR36/AR111, PAR20/PAR30, GU10**

*Remote Transformer/Line Voltage Installation*



**FOR USE WITH GU10, PAR36/AR111 and PAR20/PAR30**


7b. Aim vertically by turning the #10 Phillips head screw on OptiLock assembly with Phillips screwdriver.



**FOR USE WITH MR16, GU10, and PAR20/PAR30**

8a. Turn accessory holder upside down and remove retainer clip. Insert up to two (2) accessories. Insert the retainer clip back on.


**⚠ Insert any accessory lens with the smooth side towards the lamp. If using a honeycomb baffle, position it farthest from the lamp.**



**FOR USE WITH PAR36/AR111**


8b. Turn accessory holder upside down and remove retainer clip. Insert up to two (2) accessories. Insert the retainer clip back on.

**⚠ Insert any accessory lens with the smooth side towards the lamp. If using a honeycomb baffle, position it farthest from the lamp.**




**FOR USE WITH MR16, GU10, OR PAR20/PAR30**

9a. **For Optional Accessory Holder:** Insert accessory holder tabs into slots on OptiLock.




**FOR USE WITH PAR36/AR111**

9b. **For Optional Accessory Holder:** Insert accessory holder tabs onto arms on OptiLock.



10. Remove any dirt or debris in o-ring groove near top of housing. Place o-ring inside of groove.

**⚠ Failure to clean groove of debris will cause fixture to fail and void product warranty.**



11. Install faceplate using a 1/8" allen wrench and hand-tighten the faceplate screws in a star pattern to 30 in-lbs. min.


**⚠ Do not use a power tool to install screws. Do not exceed 40 in-lbs.**

**IMPORTANT SAFETY INFORMATION LISTED ON REVERSE  
READ, FOLLOW, AND SAVE ALL SAFETY AND INSTALLATION INSTRUCTIONS**



**Deep Housing - Standard MR16, PAR36/AR111, PAR20/PAR30, GU10**

*Lamp and Accessory Holder Installation*



Warning




Hot Surface


**TOOLS  
NEEDED:**

➤ 1/8" Allen Wrench

**Lamp Installation Or Re-Lamping**




1. Remove faceplate using a 1/8" allen wrench. If there is an optional accessory holder, carefully squeeze tabs on sides and gently pull from slots on OptiLock.



**MR16 Lamp Installation**

2a. Firmly insert proper MR16 lamp into socket to make connection.


⚠ **Do not exceed the maximum wattage listed on the fixture label before installing.**



**PAR36/AR111 Lamp Installation**

2b. Install proper PAR36/AR111 lamp by placing connectors around loosened terminal screws, then gently tightening screw to make connection.


⚠ **Do not exceed the maximum wattage listed on the fixture label before installing.**



**PAR20/30 Lamp Installation**

2c. Firmly insert proper PAR20/30 lamp into socket to make connection.


⚠ **Do not exceed the maximum wattage listed on the fixture label before installing.**



**GU10 Lamp Installation**


2d. Firmly insert proper GU10 lamp pins into socket, then gently twist to make connection.

⚠ **Do not exceed the maximum wattage listed on the fixture label before installing.**



3. Remove any dirt or debris in o-ring groove near top of housing. Place o-ring inside of groove.

⚠ **Failure to clean groove of debris will cause fixture to fail and void product warranty.**



4. Install faceplate using a 1/8" allen wrench and hand-tighten the faceplate screws in a star pattern to 30 in-lbs. min.

⚠ **Do not use a power tool to install screws. Do not exceed 40 in-lbs.**

**IMPORTANT SAFETY INFORMATION - READ, FOLLOW, AND SAVE THESE INSTALLATION INSTRUCTIONS**

**B-K LIGHTING**

40429 Brickyard Drive • Madera, CA 93636 • USA  
559.438.5800 • FAX 559.438.5900  
www.bklighting.com • info@bklighting.com

RELEASE DATE  
**10/13/2021**

REFERENCE NUMBER  
**INS-2851-00**

THIS DOCUMENT CONTAINS PROPRIETARY INFORMATION OF B-K LIGHTING, INC. AND ITS RECEIPT OR POSSESSION DOES NOT CONVEY ANY RIGHTS TO REPRODUCE, DISCLOSE ITS CONTENTS, OR TO MANUFACTURE, USE OR SELL ANYTHING IT MAY DESCRIBE. REPRODUCTION, DISCLOSURE OR USE WITHOUT SPECIFIC WRITTEN AUTHORIZATION OF B-K LIGHTING, INC. IS STRICTLY FORBIDDEN.